

Homework #9: ECE 461/661

z-Transforms, s to z conversion, Root Locus in the z-Domain. Due Monday, November 8th

z-Transforms

1) Determine the difference equation that relates X and Y

$$Y = \left(\frac{0.005z}{(z-0.98)(z-0.95)(z-0.8)} \right) X$$

2) Determine $y(k)$ assuming

$$Y = \left(\frac{0.005z}{(z-0.98)(z-0.95)(z-0.8)} \right) X \quad x(t) = 2 \cos(3t) + 4 \sin(3t)$$
$$T = 0.1$$

3) Determine $y(k)$ assuming

$$Y = \left(\frac{0.005z}{(z-0.98)(z-0.95)(z-0.8)} \right) X \quad x(k) = u(k)$$

s to z conversion

3) Determine the discrete-time equivalent of $G(s)$. Assume $T = 0.5$ second

4) Determine the discrete-time equivalent of $G(s)$. Assume $T = 0.1$ second

$$G(s) = \left(\frac{170}{(s+0.47)(s+3.40)(s+9.00)(s+16.77)} \right)$$

Root Locus in the z-Domain

Assume $T = 0.1$ seconds.

$$G(s) = \left(\frac{170}{(s+0.47)(s+3.40)(s+9.00)(s+16.77)} \right)$$

5) Draw the root locus for $G(z)$

6) Find k for no overshoot in the step response

- Simulate the closed-loop system's step response

7) Find k for 20% overshoot for a step response (damping ratio = 0.4559)

- Simulate the closed-loop system's step response

8) Find k for a damping ratio of 0.00

- Simulate the closed-loop system's step response

