

Homework #10: ECE 461/661

Digital PID Control. Due Monday, November 15th

PID Control

Assume $T = 0.5$ seconds:

$$G(s) = \left(\frac{170}{(s+0.47)(s+3.40)(s+9.00)(s+16.77)} \right)$$

1) Design a digital I controller

$$K(s) = k \left(\frac{z}{z-1} \right)$$

that results in 20% overshoot in the step response.

Simulate the step response of the closed-loop system (VisSim or Simulink preferred with $K(z)*G(s)$)

2) Design a digital PI controller

$$K(s) = k \left(\frac{z-a}{z-1} \right)$$

that results in 20% overshoot in the step response.

Simulate the step response of the closed-loop system (VisSim or Simulink preferred with $K(z)*G(s)$)

3) Design a digital PID controller

$$K(s) = k \left(\frac{(z-a)(z-b)}{z(z-1)} \right)$$

that results in 20% overshoot in the step response.

Simulate the step response of the closed-loop system (VisSim or Simulink preferred with $K(z)*G(s)$)

Meeting Design Specs

4) Design a digital controller with $T = 0.5$ seconds that results in

- No error for a step input
- 20% overshoot for the step response, and
- A 2% settling time of 10 seconds

Simulate the step response of the closed-loop system (VisSim or Simulink preferred with $K(z)*G(s)$)

5) Design a digital controller with $T = 0.1$ second that results in

- No error for a step input
- 20% overshoot for the step response, and
- A 2% settling time of 10 seconds

Simulate the step response of the closed-loop system (VisSim or Simulink preferred with $K(z)*G(s)$)